

Reg No.: _____

Name: _____

APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY

Fourth Semester B.Tech Degree (S,FE) Examination August 2021 (2015 Scheme)

Course Code: EC202**Course Name: SIGNALS & SYSTEMS**

Max. Marks: 100

Duration: 3 Hours

PART A*Answer any two full questions, each carries 15 marks.*

Marks

- 1 a) Check if the signals below are periodic. If so, find the fundamental period. (6)

(i) $x(t) = \sin(\sqrt{2}t) + \cos(t)$

(ii) $x[n] = \sin\left(\frac{2\pi n}{5}\right) + \cos\left(\frac{2\pi n}{3}\right)$

- b) Sketch the signal below. (9)

$$x(t) = e^{-a|t|}, (a > 0)$$

- (i) Represent the signal as a sum of a causal signal and an anti-causal signal.
 (ii) Determine whether it is an energy signal, power signal or neither energy nor power.

- 2 a) Determine whether the following systems are linear. (10)

(i) $\frac{d^2}{dt^2}y(t) + 3ty(t) = \frac{t^2}{2}x(t)$

(ii) $y[n] = x^*[n]$, * indicating complex conjugate

- b) A system is described by the input-output relation described below. Check (5)
 whether the system is linear and time invariant.

$$y[n] = x[kn], k \text{ a real constant.}$$

- 3 a) Find the output of the LTI system described by the impulse response (8)

$$h[n] = \begin{bmatrix} 2, 3, 3, 2 \end{bmatrix} \text{ to the input signal } h[n] = \begin{bmatrix} 1, 2, 2, 1 \end{bmatrix}$$

- b) Derive the stability condition of a continuous time LTI system having impulse (7)
 response $h(t)$.

PART B

Answer any two full questions, each carries 15 marks.

- 4 a) Consider the periodic impulse train (8)

$$\delta_T(t) = \sum_{k=-\infty}^{\infty} \delta(t - kT)$$

. Determine its

- (i) complex exponential Fourier series
(ii) Trigonometric Fourier Series

- b) Given (7)

$$x(t) \xleftrightarrow{\text{Fourier Transform}} X(\Omega),$$

show that

$$\int_{-\infty}^{\infty} |x(t)|^2 dt = \frac{1}{2\pi} \int_{-\infty}^{\infty} |X(\Omega)|^2 d\Omega$$

- 5 a) Compute the Laplace Transforms of the signals (9)

(i) $x(t) = e^{-2t} (u(t) - u(t - 5))$

(ii) $x(t) = \delta(3t + 5)$

(iii) $x(t) = e^{-2t} \cos(\Omega_0 t) u(t)$

- b) The o/p $y(t)$ of a continuous time LTI system is $y(t) = 2e^{-3t}u(t)$, when the input $x(t)$ is a unit step. Find (6)

(i) $h(t)$, the impulse response

(ii) $y(t)$, when input $x(t) = e^{-t}u(t)$

- 6 a) State and prove the sampling theorem for Low pass signals. (10)

- b) A signal $x(t) = 1 + \cos(5\pi t) + 0.5 \cos(10\pi t)$ is ideally sampled. The interval (5)
between the samples is T_s seconds. Find

(i) Maximum allowable value for T_s .

- (ii) The minimum bandwidth of the Ideal reconstruction filter. Plot its frequency response.

PART C

Answer any two full questions, each carries 20 marks.

- 7 a) A causal discrete-time LTI system is described by (10)

$$y[n] - 0.75y[n-1] + 0.125y[n-2] = x[n]$$

where $x[n]$ and $y[n]$ are the input and output of the system, respectively.

(a) Determine the system function $H(z)$.

(b) Find the impulse response $h[n]$ of the system.

(c) Find the step response $s[n]$ of the system.

- b) Show that (10)

(i)
$$x_1[n] * x_2[n] \xleftrightarrow{z} X_1(z)X_2(z)$$

(ii)
$$nx[n] \xleftrightarrow{z} -z \frac{d}{dz} X(z)$$

- 8 a) Find the DFS of the following sequences (9)

(i)
$$x[n] = \cos \frac{\pi}{4} n$$

(ii)
$$x[n] = \cos \frac{\pi}{4} n + \sin \frac{\pi}{3} n$$

(iii)
$$x[n] = \cos^2 \left(\frac{\pi}{8} n \right)$$

- b) Explain the relationship between z -Transform and DTFT (6)

- c) State and Prove the Parseval's relationship for DTFT (5)

- 9 a) Find the DTFT of $x[n] = u[n] - u[n-N]$ (8)

- b) (i) Find the impulse response of an Ideal Discrete Low Pass filter (LPF) with a (12)
cut off frequency ω_c

(ii) Is an Ideal LPF realizable in the time domain? Give reasons.
